



## HOW TO RE-CONFIGURE A QUBE SHADE NETWORK

1. Reset the Qube by holding down the blue button on the Qube for at least 30 seconds. The Qube will forget its current network configuration and wipe all data.
2. Manually reset each shade by:
  - a. Making sure the shade is at the top position by manual tug
  - b. Tug the shade 6 – 10 inches. Let go. Wait 1-3 seconds.
  - c. Tug the shade again 6-10 inches. Let go
  - d. The shade will then jog up to 25% and enter command mode.
  - e. Within 10 seconds, tug the shade 6 – 10 inches. Let go. Wait for the shade to go up to 25%.
  - f. Within 4 seconds of the 1<sup>st</sup> tug, tug the shade 6 – 10 inches. Let go. Wait for the shade to go up to 25%.
  - g. Within 4 seconds of the 2<sup>nd</sup> tug, tug the shade 6 – 10 inches. Let go. Wait for the shade to go up to 25%.
  - h. NOW, wait for the shade to automatically jog. The shade may move automatically to the top. If not, tug it less than an inch to send it to the top. The shade is ready to add back to the network.
3. Reconfigure the shade network using the Qube App, Vantage System in Design Center, or other 3<sup>rd</sup> party Platform.
  - a. Please note that in order for the shade to be in configuration mode, you must tug the shade 6-10 inches, and it will start “micro-jogging” which means it is ready to be added to a network.
  - b. QIS shades will not micro-jog from a single 6-10 inch tug after performing the tug commands reset steps. A dealer would be able to get a QIS shade to micro-jog by performing steps 2a-2e again.
  - c. If the shade does not respond, you may need to power cycle the shade to get it to respond again.

For more detailed programming instructions, please click [\[here\]](#) to learn more.